

# 1-4 Loop Fire Alarm Control Panel With Integrated Vent / Damper Control

The MxPro 5 series is fully expandable from 1 to 4 loops and supplied with 4 onboard sounder circuits, 20 programmable zonal LEDs with slide-in labels, and 25 System LEDs for information purposes. Control buttons for each damper are integrated into the front of the control panel for simple and intuitive manual control of the dampers.

The control panel consists of the latest dual flash-based microprocessor technology combined with a high resolution, high contrast, graphical LCD display and tactile keypad providing a simple select and click programming aid for engineer configuration and end-user operation. Powerful cause-and-effect programming and enhanced trace diagnostics make the panel suitable for a wide range of site applications from small to large complex multi-area systems.

Fully programmable onsite via the onboard alphanumeric keypad, or PC-Net configuration software.

**PC Software:** An extensive suite of user-friendly Windows-based PC software programs has been developed to enhance your experience when using MxPro 5 series fire panels. The suite incorporates a number of different programmes to include a configuration, service, logo and virtual panel tool to allow the flexibility of the equipment to be fully explored.

**Network:** Simply adding a network card allows the panel to communicate with any other MxPro 5 / MxPro 4 fire panel, remote terminal, or network peripherals, such as ipGateway™ or BMS/graphical interface. The network operates as a true peer-to-peer system and can be configured in a fault-tolerant loop or radial format.



- 20 programmable Zonal / 25 System LEDs.
- Hochiki protocol support.
- Advanced graphical LCD user interface and support for up to 200 fire zones by default allowing full EN54 compliance without additional hardware.
- Dedicated USB & RS232 serial port for direct PC or modem connection.
- Installer friendly Auto-learn, Loop Detection and Onboard Scope facility for ease of commissioning and fault finding.
- The graphical display can be configured to operate with virtually any language or character set and allow the installer's logo to be applied using the Logo application software.
- Integral P-Bus for system expansion via available option cards.
- Ad-Net peer-to-peer network with up to 2000 zones
- Approved to BS EN54 part 2, 4 and 13.



Specification	
Base Technology	Dual flash-based processors with real-time clock, trace diagnostics, programmable languages and character sets
Display	White backlit 240 x 64 graphical LCD
LED Indicators	22 red (1 x Fire, 1 x More Alarms, 20 x Zonal Programmable), 1 green (Power), 13 amber and 12 bi-colour (Fault & System)
Vent controls	Alpha numeric keypad permitting Navigation, Reset, Mute, Silence, Resound, Evacuate, & 4x Programmable Push buttons
Protocols	Hochiki ESP
Number Of Fire Zones	2000 (200 per individual panel)
Number Of Loops	Dedicated 1-4 loop control panel
Devices Per Loop	126
Loop Current	500mA per loop
On-Board Sounder Circuits	4 x 1 Amp programmable
On-Board Relays	2 x 1 Amp 30v AC/DC programmable (10mA, 5v min) - expandable to 4 using MXP-507
Auxiliary Supply	1 x 24v 500mA
Programmable Input	1 x monitored programmable input on-board
Programmable Key Switch Inputs	8 volt free inputs
Total Available Output Current	5A maximum available for loop current + sounder outputs + auxiliary supply
Mains Supply	200 - 240v 47-63 Hz AC (+10%, -15% tolerance) 1.4A max
Charger Current	2A temperature compensated
Serial Ports	1 x on-board RS232 connection for PC, modem, IP or portable printer
USB Interface	1 x USB B type connection for PC communication
Programming	On-board keypad or PC running Windows tools
Event Log	5000 Event & Diagnostic + 500 Fire
Networking	Optional plug in network card (MXP-503 - standard, or MXP-509 - fault-tolerant)
Enclosure / Colour	Steel IP30 / RAL7035
Medtalwork Options	Flushing bezel, battery box, utility enclosure, termination enclosure and rack mount
Approvals	EN 54-2:1998, EN 54-4:1998 & EN 54-13:2005